

SmartPro 230V 3kVA 2.7kW Line-Interactive Sine Wave UPS, 2U, Extended Run, Network Card Options, LCD, USB, DB9

MODEL NUMBER: SMX3000XLRT2UA











Description

Tripp Lite SmartPro Line Interactive UPS with enhanced LCD interface offers network-grade power protection for critical server, network and telecommunications equipment. Line Interactive Uninterruptible Power Supply (UPS) with built-in Auto-Voltage Regulation (AVR) actively corrects brownouts and overvoltages back to usable levels while maintaining a full battery charge in case of power failure. Tripp Lite's unique configuration excels in exceptionally poor-power environments with two separate levels of voltage boost to correct both slight undervoltages and severe brownout conditions. Interactive LCD interface reports UPS operating mode, detailed UPS and site-power data, plus enables a variety of UPS setup and configuration options. Super-fast switchover

Highlights

- 3kVA / 3000VA / 2700W line interactive 2U rack/tower UPS, Sine Wave
- 230V output, Corrects brownouts and overvoltages from 158V to 278V
- 0.9 Power Factor, Interactive
 LCD interface
- Extended runtime options up to 2700W
- 4 post compatible mounting accessories
- 98% line-mode efficiency, 2 switched load banks
- USB, RS232, EPO and slot for Network Management Card options
- 230V C20 inlet, 8 C13 & 1 C19 outlets

Package Includes

- SMX3000XLRT2UA UPS system
- USB, Serial & EPO cabling
- 4 post rackmount installation kit
- Set of 3 C13/C14 power cables
- Instruction manual

from line to battery power occurs within milliseconds to maintain operation of connected equipment without interruption or reboot. 98% line-mode efficiency offers reduced heat emissions and operating costs. Network management interfaces support communications via USB, RS-232 and slot for network management card option. HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X. Network communications ports enable detailed monitoring of equipment load levels, self-test data and utility power conditions. PowerAlert monitoring software is available for free download. Switched output load banks enable scheduled and real-time remote reboot and load shedding of select outlets. Emergency Power Off (EPO) interface. LCD display panel easily rotates for viewing in rackmount or tower configurations. Audible alarm with push-button momentary alarm-cancel and silent-mode configuration options. Programmable self-test. Field-replaceable, hot-swappable battery modules.

Features

- Tripp Lite SMX3000XLRT2UA line interactive 2U rack/tower UPS with 3000VA / 3kVA capacity and extended runtime options
- Line interactive UPS with Automatic Voltage Regulation (AVR) corrects brownouts and overvoltages from 158 to 278V
- C20 AC power inlet; 8 C13 and 1 C19 output receptacles, Two independently switchable output load banks
- Maintains uninterrupted operation of connected networking equipment during blackouts, surges, brownouts and overvoltages
- High 98% efficiency rating in line-power mode offers reduced power consumption and BTU emisssions
- Internal batteries offer 11.1 minutes at 50% load (1350W) and 3.9 minutes at 100% load (2700W)
- Extended runtime is available with optional external battery packs BP48V24-2U (limit 1), BP48V60RT-3U (multi-pack compatible) and BP48V27-2US (multi-pack compatible)



- External battery configurations require the use of Tripp Lite's External Battery Configuration Software (see manual)
- Hot-swappable, user-replaceable internal batteries and external battery packs can be replaced with no disruption to connected equipment
- Intelligent battery management system extends battery life
- Front panel LCD monitoring screen with MODE and ENTER buttons reports operating mode with 5-bar battery charge graphic, plus 7 selectable screens of detailed UPS and site power information
- LCD interface also supports a number of advanced user setup and operating preferences
- Ships with 4 post rackmount installation hardware; Optional 2POSTRMKITWM enables 2 post rackmount/wallmount installation; Optional 2-9USTAND enables tower placement
- Built-in USB, RS-232 and slot for optional network management card options
- Compatible with Tripp Lite UPS management card options TLNETCARD, WEBCARDLX, SNMPWEBCARD and RELAYIOCARD
- HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X
- USB & Serial ports enable data-saving unattended shutdown when used with Tripp Lite's PowerAlert software, available via FREE download from www.tripplite.com/poweralert
- Built-in Emergency Power Off (EPO) interface with cable

Specifications

OUTPUT		
Output Volt Amp Capacity (VA)	3000	
Output kVA Capacity (kVA)	3	
Output Watt Capacity (Watts)	2700	
Output kW Capacity (kW)	2.7	
Power Factor	.9	
Nominal Output Voltage(s) Supported	220V; 230V; 240V	
Nominal Voltage Details	230v nominal inverter output voltage	
Frequency Compatibility	50 / 60 Hz	
Output Voltage Regulation (Line Mode)	+6%, -15%	
Output Voltage Regulation (Battery Mode)	+/-5%	
Output Receptacles	(8) C13; (1) C19	
Included Output Power Cables	Set of 3 C13 to C14 power cables included	
Load Management Receptacles	Two switchable single outlet C13 load banks	
Output AC Waveform (AC Mode)	Pure Sine wave	
Output AC Waveform (Battery Mode)	Pure Sine wave	
INPUT		
Rated input current (Maximum Load)	14.1A	
Nominal Input Voltage(s) Supported	230V AC 2/5	





UPS Input Connection Type	C20 inlet
UPS Input Connection Description	IEC320-C20 input connection accepts a variety of user supplied detachable C19 output cordsets to match country or site specific power sources
Input Circuit Breakers	20A
Input Phase	Single-Phase
BATTERY	
Full Load Runtime (min.)	3.9 min. (2700w)
Half Load Runtime (min.)	11.1 min. (1350w)
Expandable Battery Runtime	Extended runtime supported via optional external battery packs
External Battery Pack Compatibility	BP48V24-2U(limit 1); BP48V60RT-3U(multi-pack compatible); BP48V27-2US(multi-pack compatible)
DC System Voltage (VDC)	48
Battery Recharge Rate (Included Batteries)	Less than 5 hours from 10 to 90% (typical, full load discharge)
Internal UPS Replacement Battery Cartridge	RBC58-2U
Battery Access	Front panel battery access door
Battery Replacement Description	Hot-swappable, replaceable batteries
Expandable Runtime	Yes
VOLTAGE REGULATION	
Voltage Regulation Description	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 158 to 278
Voltage Regulation Description Overvoltage Correction	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 158 to 278 Input voltages between 244 and 278 are reduced by 12%
Overvoltage Correction	Input voltages between 244 and 278 are reduced by 12%
Overvoltage Correction Undervoltage Correction	Input voltages between 244 and 278 are reduced by 12% Input voltages between 206 and 183 are boosted by 12% Input voltages between 158 and 183 are boosted by 24%
Overvoltage Correction Undervoltage Correction Severe Undervoltage Correction	Input voltages between 244 and 278 are reduced by 12% Input voltages between 206 and 183 are boosted by 12% Input voltages between 158 and 183 are boosted by 24%
Overvoltage Correction Undervoltage Correction Severe Undervoltage Correction USER INTERFACE, ALERTS & CON	Input voltages between 244 and 278 are reduced by 12% Input voltages between 206 and 183 are boosted by 12% Input voltages between 158 and 183 are boosted by 24% ITROLS Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual
Overvoltage Correction Undervoltage Correction Severe Undervoltage Correction USER INTERFACE, ALERTS & CON Front Panel LCD Display	Input voltages between 244 and 278 are reduced by 12% Input voltages between 206 and 183 are boosted by 12% Input voltages between 158 and 183 are boosted by 24% ITROLS Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options)
Overvoltage Correction Undervoltage Correction Severe Undervoltage Correction USER INTERFACE, ALERTS & CON Front Panel LCD Display Switches	Input voltages between 244 and 278 are reduced by 12% Input voltages between 206 and 183 are boosted by 12% Input voltages between 158 and 183 are boosted by 24% ITROLS Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options) 3 pushbutton switches control OFF / ON power status, MODE selection and MUTE / ENTER control functions Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option
Overvoltage Correction Undervoltage Correction Severe Undervoltage Correction USER INTERFACE, ALERTS & CON Front Panel LCD Display Switches Alarm Cancel Operation	Input voltages between 244 and 278 are reduced by 12% Input voltages between 206 and 183 are boosted by 12% Input voltages between 158 and 183 are boosted by 24% ITROLS Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options) 3 pushbutton switches control OFF / ON power status, MODE selection and MUTE / ENTER control functions Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option available
Overvoltage Correction Undervoltage Correction Severe Undervoltage Correction USER INTERFACE, ALERTS & CON Front Panel LCD Display Switches Alarm Cancel Operation Audible Alarm	Input voltages between 244 and 278 are reduced by 12% Input voltages between 206 and 183 are boosted by 12% Input voltages between 158 and 183 are boosted by 24% ITROLS Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options) 3 pushbutton switches control OFF / ON power status, MODE selection and MUTE / ENTER control functions Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option available
Overvoltage Correction Undervoltage Correction Severe Undervoltage Correction USER INTERFACE, ALERTS & CON Front Panel LCD Display Switches Alarm Cancel Operation Audible Alarm SURGE / NOISE SUPPRESSION	Input voltages between 244 and 278 are reduced by 12% Input voltages between 206 and 183 are boosted by 12% Input voltages between 158 and 183 are boosted by 24% Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options) 3 pushbutton switches control OFF / ON power status, MODE selection and MUTE / ENTER control functions Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option available Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown conditions



PHYSICAL		
Included Mounting Accessory Description	4 post rackmount installation hardware included	
Installation Form Factors Supported with Optional Accessories	2 post rackmount(2POSTRMKITWM); Wallmount(2POSTRMKITWM); Tower(2-9USTAND)	
Primary Form Factor	Rackmount	
UPS Power Module Dimensions (hwd, in.)	3.5 x 17.5 x 19.5	
UPS Power Module Dimensions (hwd, cm)	8.89 x 44.45 x 49.53	
Rack Height (U Spaces)	2	
Minimum Required Rack Depth (inches)	26.5	
Minimum Required Rack Depth (cm)	67.31	
UPS Power Module Weight (lbs.)	62.8	
UPS Power Module Weight (kg)	28.49	
UPS Shipping Dimensions (hwd / in.)	9 x 23.75 x 20.5	
UPS Shipping Dimensions (hwd / cm)	22.86 x 60.32 x 52.07	
Shipping Weight (lbs.)	72.6	
Shipping Weight (kg)	33	
Cooling Method	Fan	
UPS Housing Material	Steel	
Minimum Required Rack Depth (mm)	673	
Primary UPS Height (mm)	89	
Primary UPS Width (mm)	444	
Primary UPS Depth (mm)	495	
Shipping Height (mm)	229	
Shipping Width (mm)	603	
Shipping Depth (mm)	521	
ENVIRONMENTAL		
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius	
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius	
Relative Humidity	0 to 95%, non-condensing	
AC Mode BTU / Hr. (Full Load)	158	
Battery Mode BTU / Hr. (Full Load)	1501	





AC Mode Efficiency Rating (100% Load)	98%	
COMMUNICATIONS		
Communications Interface	USB (HID enabled); DB9 Serial; EPO (emergency power off); Slot for SNMP/Web interface	
Network Management Cards	SNMPWEBCARD; TLNETCARD; WEBCARDLX; RELAYIOCARD	
Network Monitoring Port Description	Supports detailed monitoring of UPS and site power conditions	
PowerAlert Software	For local monitoring via the UPS's built-in communication ports, download PowerAlert Local software at http://www.tripplite.com/poweralert	
Communications Cable	USB, DB9 and EPO cabling included	
WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications	
LINE / BATTERY TRANSFER		
Transfer Time	6 milliseconds (AC to battery mode), 1 millisecond (Battery to AC mode)	
Low Voltage Transfer to Battery Power (Setpoint)	158	
High Voltage Transfer to Battery Power (Setpoint)	278	
SPECIAL FEATURES		
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported	
High Availability UPS Features	Hot swappable batteries	
Green Energy-Saving Features	Greater than 95% efficiency - GREEN UPS; Individually controllable load banks; Schedulable daily hours of economy mode operation	
CERTIFICATIONS		
UPS Certifications	CE; ROHS (Restriction of Hazardous Substances)	
UPS Certification Details	IEC 62040-1, IEC 62040-2 Class A EMI, GOST	
WARRANTY		
Product Warranty Period (Worldwide)	2-year limited warranty	
	I.	

© 2017 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: https://www.tripplite.com/products/product-certification-agencies